
63mm
60mm
29mm
31.5mm
30mm
14.5mm
10mm
7mm
23mm
117.555mm
2mm
3mm
4mm
3mm
3mm
13mm
2mm
3mm
3mm
3mm
3mm
3mm
3mm
18mm
2.0mm
12mm
1.5mm
5mm
10mm
43mm
10mm
10mm
1
2
3
4
5
MORE STARS
MORE SAVINGS
POWERSA VINGS
GUIDE
ENERGY EFFICIENCY
91*
DC-AC
Label Period : 1st Jan 2017 - 31st Dec 2019
Appliance : Inverters
Brand : XX
Model/Year : XX/YYYY
Technology : XX
Waveform : XX
Capacity (VA) / (Watts) : XX / XX
BEE/XYZ/XX
Under test Conditions, when tested in accordance with IS 13314.
Actual Performance will depend on how the appliance is being used.


BlackOutline(Outer).5pt
BlackOutline(Inner)1.5pt
Yellow Y:40
StarOutlineBlackK:30
7.5pttextBlack(ArialBlack)
Red
Yellow Y:40
Black15pttextwhite
Yellow Y:20
Outline1pt
Blacktext6pt(ArialBlack)
Green1 1ptWhitetext(ArialBlack)
Blacktext6pt(ArialBlack)
Blacktext6pt(ArialBold)
Blacktext6pt(ArialBold)
Green C :81, M:10,Y:90, K:1
BlueC:97,M:95, Y:6,K:1
Blacktext4pt(Arial)
Black5pttext(ArialNarrow)
Outline.5pt
MORE STARS
MORE SAVINGS
POWERSA VINGS
GUIDE
ENERGY EFFICIENCY
91*
DC-AC
Label Period : 1st Jan 2017 - 31st Dec 2019
Appliance : Inverters
Brand : XX
Model/Year : XX/YYYY
Technology : XX
Waveform : XX
Capacity (VA) / (Watts) : XX / XX
BEE/XYZ/XX
Under test Conditions, when tested in accordance with IS 13314.
Actual Performance will depend on how the appliance is being used.


MORE STARS
MORE SAVINGS
POWERSA VINGS
GUIDE
ENERGY EFFICIENCY
91*
DC-AC
Label Period : 1st Jan 2017 - 31st Dec 2019
Appliance : Inverters
Brand : XX
Model/Year : XX/YYYY
Technology : XX
Waveform : XX
Capacity (VA) / (Watts) : XX / XX
BEE/XYZ/XX
Under test Conditions, when tested in accordance with IS 13314.
Actual Performance will depend on how the appliance is being used.